

Overview

The Fitness Audio Digital DX6 Series is our latest wireless mic receiver and transmitter combo. The transmitter has been made smaller and more functional.

The DX6-R incorporates ASAP® (Auto Search Auto Pair) technology for an instant start on an interference free channel. No set-up is required. Mic signals pass through a seamless 3-stage data redundancy circle to ensure stable and quality reception. A proprietary codec (encode/decode) circuit ensures excellent audio quality and a wide dynamic range.



Features

- Dual receiver to allow two transmitters to be connected at one time.
- Clear and intuitive LCD display for easy operation and quick set-up.
- Digital Sound Processing - More gain, less feedback.
- 82 Channel auto scan to find the cleanest channel.
- Sleek/Compact design with sweat protection.
- Operating time up to 12 hours with 2 x AA batteries.
- No antenna on the transmitter.
- Sturdy ABS housing.

Product Specifications

Type	Wireless Microphone Transmitter & Receiver
Power Requirements	12vDC 2000ma (Power Adaptor Included)
Frequency	2.4ghz
Connector	2 x XLR (Mic 1 & Mic 2) + Combined TRS (Mic / Line Level) Output
Dimensions & Weight	200mm x 150mm x 44mm (LxWxH) 530g
Net Weight	60g (2.11oz)

